



Wire Connector Instructions

WARNING – SHOCK HAZZARD

Contact with electricity can cause electrical fires, serious injury or death. Shut off power to the circuit or remove fuse before using this product.

SAFETY NOTICE

Improperly installed electrical wiring can be dangerous and cause electrical fires. The connector chosen must be sized to the wires being used. Consult local building codes before doing any electrical wire and to determine installation requirements. For assistance, refer to an instructional book for electrical installations or consult a qualified electrician.

To be sold only with installation instructions.

Installation Instructions

1. Turn off power before removing or installing connectors.
2. Strip connectors to the correct strip length per the chart below:

Connector	Strip length
WC-16R	Strip wires 5/16" (8mm)
	Strip wires #16 and smaller strip 3/8" (9.5 mm)
WC-14R	Strip wires 3/8" (9.5 mm)
	Strip #16 and smaller 7/16" (11 mm)

3. Straighten and align frayed strands.
4. Hold wires together with ends even. Lead stranded wires slightly ahead of solid wires.
5. Pre-twisting acceptable, but not required. For pre-twisting, strip wires long, hold wires together with insulation even, twist wire ends together, trim to recommended strip length.
6. Insert bundle into connector and twist clockwise until tight.
7. Insert twist-on connector deep into the thermoplastic protective shell tube.
8. Position wires into the designated wire channels on the lip of the latch and lock the cap into place for a secure connection.

Use only on Copper to Copper (Cu/Cu) wire combinations.

For use in dry locations only.

Temperature rating: 105°C (221°F) maximum.

*300 volts maximum

**600 volts maximum building wire; 1000 volts signs or lighting fixtures.

